

## PX-4120

All-in-one 4 zones analog matrix with amplification and integrated sources



PX-4120

### PX-4120

- It has 4 amplifiers of 120W each, 100/70V or 4Ω, a tuner, an USB/SD player, a 3 combo XLR/JACK 6.35 MIC/LINE input with phantom power supply, 2 RCA auxiliary input and a TEL IN input on a terminal block.
- First input has a talk over priority and TEL IN input have an over priority.
- Up to 4 selective call mic stations RM-4012 can be linked with a CAT5 cable.
- Each input can be affected on one or several zones and it has an adjustable level, tone, and a mute function.
- Each zone has an independent volume control, a bargraph and a balanced 0dB output to connect an additional amplifier and can be monitored by an 8Ω speaker.

### RM-4012: 4 zones selective call mic station for PX-4120 amplified matrix



### RM-4012

- It can be linked to a maximum of 4 stations, by using a CAT5 cable up to 100m without power supply. Beyond 100m a 220V power supply is included with the station.
- It is equipped with a 2 or 4 tone chime with level control, with a lighting ring and an output level bar graph.

Model	PX-4120
Zones	4
Outputs power	4 x 120W 100/70V or 4Ω
Inputs	CH1/2/3 combo XLR/JACK 600Ω Balanced CH5, 6 RCA stereo 10kΩ Unbalanced TEL IN : terminal block 10kΩ
Bandwidth	80 to 16,000
THD	< 1%
Signal / noise	> 65dB
MP3	Max. capacity of 32GB
Recording format	WAV
Power source	220V - 50/60Hz
Consumption	750W
Dimensions (WxHxD)	484 x 132 x 440mm
Weight (kg)	11.68



RM-4012 rear panel

Model	RM-4012
Zones	4
Communication	RS-485 (max. 1km)
Cap	Electret Unidirectional
THD	< 1%
Bandwidth (Hz)	80 to 18,000
Power source	24V DC supplied
Dimensions (WxHxD)	197 x 43 x 115mm
Weight (kg)	0.990



PX-4120 rear panel

**MAJORCOM** ●

56, chemin de la Flambère · 31300 Toulouse · FRANCE · Tél. 33 (0)5 61 31 86 87  
Fax 33 (0)5 61 31 87 73 · commercial@majorcom.fr · www.majorcom.fr