

L-1800 : 2 x 360W - 8Ω / 2 x 600W - 4Ω amplifier

L-2400 : 2 x 500W - 8Ω / 2 x 750W - 4Ω amplifier



L-1800

- High quality low impedance amplifier which can deliver a power of 2x 650W under 4Ω and can be bridged to obtain 1800W under 4Ω.

L-2400

- High quality low impedance amplifier which can deliver a power of 2x 750W under 4Ω and can be bridged to obtain 2400W under 4Ω.

They are equipped with :

- a protective circuit against overloads and short circuits
- a high-pass active filter to protect speakers from very low frequencies < 50Hz or < 30Hz to be selected
- an input limiter that can be activated with a switch
- a display of modulation by LED (protection, saturation, modulations).

| Model | L-1800 | L-2400 |
|--------------------|--|--|
| Power | 2 x 360W RMS under 8Ω 2 x 600W RMS under 4Ω 1,200W RMS bridged under 8Ω 1,800W RMS bridged under 4Ω | 2 x 500W RMS under 8Ω 2 x 750W RMS under 4Ω 1,500W RMS bridged under 8Ω 2,400W RMS bridged under 4Ω |
| Bandwidth | 20Hz - 20kHz ±1dB 5Hz - 70kHz ±3dB | |
| T.H.D | < 0.03% | |
| Channel separation | > 80dB | |
| Residual noise | < -85dB | |
| Signal / Noise | > 100dB | |
| Input sensitivity | 3,5dBu | |
| Output circuit | Class-H | |
| Protection | Thermal, short circuit | |
| Power source | 220V - 4A | 220V - 4,5A - 50Hz |
| Dimensions (WxHxD) | 482 x 88 x 369mm | |
| Weight | 15kg | |



Rear panel

FICHE SPEAKON NL4

Input and link by 4-pole male SPEAKON plug (optional)