

# PP-6214

## Preamplifier mixer 10 inputs, 2 outputs



- The PP-6214 is a 2-output Pre-amplifier / Mixer which allows any of the unit's 10 input signals to be routed to Output 1, Output 2 or both.
- It is ideal for dual zone public address or audio visual installed applications such as factories, leisure centres, hotels and general PA systems.
- It has 8 Mic inputs (CH 1 to CH 8), 7 Line inputs (CH 2 to CH 8), 2 Stereo inputs and 2 Priority input.
- Phantom power (18v block switched) can supply 8 Mic inputs and a 3-band equalizer per output allows you to make correction independently on the 2 outputs.
- It can be supplied by a 24VDC backup power supply.

| Model              | PP-6214  |
|--------------------|--|
| Inputs             | MIC (CH 1 à CH 8) : XLR -60dB / 600Ω - LINE (CH 2 à CH 8) : Jack mono 6.35mm -30dB / 10kΩ<br>STEREO : RCA -30dB / 10kΩ |
| Outputs            | XLR +4dBm / 600Ω   |
| REC outputs        | -6dB / 10kΩ  |
| Bandwidth          | 20Hz - 20kHz   |
| Phantom            | MIC 1 à 8 : 18VDC  |
| Power source       | 230VAC 50Hz - 24VDC  |
| Dimensions (WxHxD) | 482 x 88 x 280mm · 2U  |
| Weight             | 5.5 kg   |



Rear panel