

DSA-500Q / DSA-2000Q

300W / 8Ω - 500W/4Ω - 1000W/8Ω bridged amp with DANTE™ network and DSP incorporated

1200W / 8Ω - 2000W / 4Ω - 4000W / 8Ω bridged amp with DANTE™ network and DSP incorporated



You can easily configure the DSA-500Q and DSA-2000Q and DSP remotely via PC

- DSA-500Q & DSA-2000Q are 4-CH high power and high quality professional amplifiers which incorporate a DSP, Digital Signal Processor and Audinate's Dante™ digital audio network.
- DANTE™ delivers low latency, robust synchronization, I/O scalability, and installation simplicity via standard IT technology.
- Easy control of equipment through front panel with OLED and PC GUI.
- Simultaneous control of multiple amplifiers via PC GUI.
- Up to 340ms delay time adjustable.
- Unlimited preset creation for environment-optimization.

Model	DSA-500Q	DSA-2000Q
Rated Power -20ms burst (Static)	8Ω, Stereo Mode	300W
	4Ω, Stereo Mode	500W
	2Ω, Stereo Mode	800W (400W)
	8Ω, Mono Mode Bridged	1,000W
	4Ω, Mono Mode Bridged	1,600W (800W)
Input Sensitivity	+4dBu	+10dBu
Gain (Stereo, Mono)	32dB	
Gain (Bridged)	38dB	
S/N	> 92dB	
THD (1/3W Rated power)	< 0.5%	< 0.7%
Bandwidth (1W, 0±2dB / 8Ω)	20Hz to 20,000Hz	
DSP Precision	32bit Fixed Point(8.24 format)	
A/D, D/A	24bit conversion, sampling rate: 48kHz	
DSP Function	Input gain, Parametric EQ, HPF, LPF, Limiter, Delay	
Consumption	390W (1/8 rated power @ 2Ω)	700W (1/8 rated power @ 2Ω))
Power source	AC 220-240V, 50/60Hz	
Operating Temperature/Humidity	-10°C~+40°C / 0%~90%	
Dimensions (WxHxD)	482 x 88 x 420mm	
Weight	10.48kg	11.79kg



Rear panel



FICHE SPEAKON NL4

Input and link by 4-pole male SPEAKON plug (optional)