DW-BT

Dante™ Wall-Mount plate : Bluetooth, RCA, Mini jack

Dante DW-BT is a wall-mount plate for converting analog audio signals, Bluetooth into digital Dante signals over the network. Ideal for long distance audio transmission over the network.

- RJ45 CAT5/6 port with PoE power to connect to the Dante network and controlled by Audinate's Dante Controller software
- Advanced Bluetooth version 5 technology. Bluetooth easy to pair by pressing the PAIR button (compatible with a wide variety of cell phones, tablets, computers and other devices).
- With stereo RCA and 3.5mm mini jack input
- With a stereo output in mini jack 3.5 mm

Model	DW-BT
Dante audio channels	x4
Input interface	Bluetooth 5.0 / 2x RCA stereo / Mini-jack 3.5 mm
Output interface	Bluetooth 5.0, stereo, 3.5 mm TRS*1
Signal to noise ratio	>100dB
Noise floor	-90dB
Power consumption	2W
THD	Less than 0,005 %
Frequency response	20~20KHz
Power supply	POE
Operating temperature	-10°C - 40°C
Operating humidity	5-95%
Dimensions	123.5×109.1×30mm

www.majorcom.fr commercial@majorcom.fr +33 [0]5 61 31 86 87 MAJORCOM