PM-835

USB, BT, FM, AUX IN, Micro SD Wall Multimedia Plate - 2 x 10W - 8Ω

- Standard case 86mm, sleek design with LED screen
- Integrated high efficiency amplifier 2x10W at 8Ω
- · Built-in music source: USB, Micro SD, Bluetooth and FM, AUX inputs and outputs
- · Can store 20 radio channels, supports automatic and manual search
- Bandwidth: 20Hz ~ 20kHz for an excellent musical effect
- · With IR remote control for more convenient use






- The PM-835 is a practical and effective wall-mounted multimedia player. With a neat and refined design, this wall plate offers you many audio sources, including FM radio, a micro SD card reader, a Bluetooth receiver, and a USB drive, AUX1 auxiliary input and AUX2 auxiliary output.
- The PM-835 supports the most common audio formats such as MP3, WMA, WAV, AAC, FLAC, etc. and the FM radio can store and store up to 20 radio stations.
- This multimedia player also includes a digital amplifier Class D type which delivers a power of 2x10W RMS with an impedance of 8Ω with a frequency response of 20Hz-
- This deck also comes with an infrared remote control for convenient and comfortable use, its LED display screen allows you to see the selected source, time, title and the total number of songs on the screen.

Model	PM-835
Output power	2 X10W
Impedance	8Ω
Harmonic Distortion Rate	≤0.03% (1kHz, 1W, 8Ω)
Signal to Noise ratio	> 81dB
Frequency response	20Hz -20kHz
Max capacity Micro SD card	32GB
Audio Format	MP3, WMA, WAV, AAC, FLAC
Bluetooth	BT2.1+EDR
Power	AC 100-240V/50-60Hz
Dimensions (W x H x D)	86 x 86 x 38mm
IR Remote control	Range 8-12m A +/-60 ° directionality
AUX1 Input Sensitivity	Stereo Unbalanced odB
AUX2 Output Sensitivity	Stereo Unbalanced odB

AUX 220VAC 8Ω output Input (Antenna) I Output



Mounting surface included



In Wall Mounting (optional) **BOITIER PM E**



