

CX-2310

2-band stereo active filter



- It's a professional quality active filter.
- It allows to distribute an input signal to adjustable frequency band. The signal can be separated into 2 bands on stereo mode and 3 bands on mono with subwoofer output.
- Its low noise electronic system and its precision potentiometers make it a high quality filter.

Model	CX 2310
Number of outputs	2 bands stereo / 3 bands mono
Input Output	balanced
Linkwitz-Riley Filter	24dB/octave
Level adjustment	on each band
Phase inverter	yes
Mute button	for each band
Low-cut filter	< 25Hz
Power source	240VAC - 50Hz
Consumption power	< 17W
Dimensions (WxHxD)	482 x 44 x 217mm
Weight	3kg



Rear panel