

MICHF-PRO CRAV-S

Wireless lavalier microphone transmitter and receiver set



- It delivers excellent audio quality with a frequency response close to the wired version and offers up to 12 compatible frequencies per band.
- Quick and easy to install thanks to its integrated antennas.
- The rack-mountable receiver with detachable antennas enable the use of antenna offsets and antenna distributors, and is ideal for cost-effective fixed installation.
- Regardless of the environment, the QuickScan function will find the best possible frequency ensuring a stable transmission.
- Simple and complete system for speakers and actors.
- Composed of a receiver with single and double rack mounting kit and front-mounted antennas, a bodypack transmitter equipped with a cardioid static tie microphone.

Model	MICHF-PRO CRAV-S
Transmitter screen display	no
Power	Transmitter : 2 AA batteries, Receiver : power supply
Removable antennas	yes
Autonomy	Up to 14 hours
Bandwidth	M17- 662 to 686 MHz
Capsule	static
Interchangeable capsule	no
Category	complete lavalier microphone system
Transmit encryption	no
Directivity	cardioid
Max number of concurrent systems	12
Transmission coverage	100 m
RF Transmitter Output	10 mW
Audio Frequency Response	50 Hz - 15 kHz
Frequency scanner	yes
Transmitter sync	QuickScan
Transmission	analog
Screen	LCD display on the receiver with detailed RF and audio metering
Housing	Transmitter : molded ABS / Receiver : molded ABS and metal
Audio output level	adjustable
Antennas	1/4 wave detachable
Included accessories	windscreen, tie clip, single and double rack mounting kit, front-mounted antennas