

PATL-100

100V to audio line level converter



- Box for connecting a 100V audio signal source to devices with line input
- Adjustable line output level (0-5.6V at 100V input voltage), can be switched internally for other output voltages
- 100V input with plug-in screw terminal

- Balanced XLR output, impedance: 1k Ω , XLR panel plug
- Insulated plastic housing
- Galvanically isolated input and output

Model	PATL-100
Input	Screw terminal (100V)
Output	XLR, balanced
Output signal	0-1.5V
Operating temperature	0°C ~40°C
Dimensions (WxHxD)	171 x 81 x 61mm
Weight	0,520kg